

This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problem Mailbox.**

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention generally relates to testing of integrated circuits, and more particularly, to the debugging of complex application specific integrated circuits (ASICs).

2. Description of the Related Art

Many modern electronic devices are now implemented using application specific integrated circuits (ASICs). ASICs are computer chips designed for a specific application, and are typically built by connecting existing circuit building blocks. Since the building blocks may already exist in a library, it is much easier to produce a new ASIC than to design a new chip from scratch. As the feature size of integrated circuits has grown smaller, the level of integration (i.e., the number of gates) available in ASICs has grown. With this increase has come increased complexity in all stages of the integrated circuit (IC) design process, particularly the testing phase.

Testing ASICs means more than just designing for test. Although today's sophisticated design-for-test (DFT) tools are a big step forward from earlier ones, testing is still a difficult process. One area of particular concern is trying to make sure that the devices will be testable when the silicon finally arrives. For complex designs this requires much more than just the utilization of an automatic-test pattern-generation (ATPG) package. Even with these automated tools, test-development can still take months and, in the case of mixed-signal ICs, sometimes stretches to over a year.

Very complicated ASICs (e.g., those with over a million gates), are particularly difficult to debug. This problem is exacerbated when the test is performed when the ASIC is in a system. The potential errors can be hard to identify due to the very low visibility into the chip. One prior art solution to this problem is functional, or edge-connector test. In this test a system board is coupled to test hardware (e.g., a programmable test computer), that applies particular input to the board and then monitors the board's output to see if the expected results are obtained. This method has a number of drawbacks. First, the test code must generally be manually written. Also, the test code may be slow, depending on how long it takes to get the board set up to the particular test

state. Furthermore, the testing is based on the board function, not the underlying circuit structure. Finally, the testing is typically limited to input/output (I/O) only, since only I/O ports are visible with this method.

A second prior art solution is a so-called in-circuit test using a bed-of-nails tester. 5 A bed-of-nails-tester uses expensive testers and fixtures that physically connect to test points on a board. While this method gives better test resolution than the edge-connector test, it too has a number of limitations. First is the high cost of having custom fixtures made. Second, some modern boards are difficult to test with these testers (e.g., double-sided boards, those with fine lead pitch devices). Finally, the tests are still limited to the 10 device stage (i.e., there is no way to see inside a complex ASIC).

In order to address a number of these drawbacks, a third solution called boundary scan technology was developed. ICs designed to support boundary scan functionality typically include a set of control and data pins which allow test data and results to be shifted into and out of the device. The test paths within the devices allow certain 15 registers to be preloaded with test patterns, and then the device can be clocked and the results shifted out. One organization, the Joint Test Action Group (JTAG) developed a standard for boundary scan technology in the mid 1980's (now IEEE Std. 1149.1).

While JTAG provides a substantial improvement over other prior art test methods, it still does not satisfy all test needs, particularly for highly complex high-speed ASICs. 20 In particular, it is difficult to monitor in real-time the inner workings of an ASIC being tested because the boundary scan methodology typically utilizes a serial shift out of test data on the ASIC's own output pins. In addition, there are no provisions for allowing direct real time access to wide internal buses deep within the ASIC. For these reasons, a system and method for allowing real time observability into complex ASICs is needed.

25

SUMMARY OF THE INVENTION

The problems outlined above may at least in part be overcome by a system and method for testing integrated circuits in accordance with the present invention. In one embodiment, such a system and method utilize special logic that allows the multiplexing of different critical busses so that the signals on the critical busses may be output for observation via selected test pins on the integrated circuit. Unlike prior art boundary scan devices, the information from the selected critical bus may be output in parallel in real time. Advantageously, this may make testing and/or debugging the integrated circuit design more accurate and less time consuming.

In one embodiment, an integrated circuit utilizing the system for testing may include a plurality of functional units connected by a plurality of internal buses. The integrated circuit may include a plurality of pins ("functional pins"), typically located on the periphery of the integrated circuit, used for interfacing with other integrated circuits or devices. In order to enable efficient and accurate testing and debugging of the functional blocks, it may be advantageous to be able to monitor signals on some or all of the internal busses connecting some or all of the functional units. To accomplish this, the integrated circuit may also include one or more control pins and/or test pins, also typically located on the periphery of the integrated circuit, used for debugging the ASIC. The integrated circuit may also include multiplexing logic comprised in the integrated circuit and connected to some or all of the internal buses and/or functional units. The multiplexing logic may be configured to select one of the internal buses or functional units in response to one or more control signals conveyed to the multiplexing logic via the control pins. The multiplexing logic may be configured to output signals from the selected internal bus or functional unit to the test pins in real-time and preferably in parallel.

In some implementations, the multiplexing logic may be configured to switch slowly relative to the internal buses and/or functional units. Advantageously, this may allow the multiplexing logic to be implemented on the integrated circuit using smaller transistors, thereby preserving precious real estate on the die.

A method for testing integrated circuits is also contemplated. In one embodiment, the method includes conveying one or more control signals to one or more test control pins on an integrated circuit that is to be tested. The control signal or signals cause the selection logic within the integrated circuit to select one of a plurality of internal buses and/or functional units for output to a set of parallel output pins on the integrated circuit. Software for automatically determining the size of multiplexing logic to allow a particular set of internal buses and/or states to be individually monitored is also contemplated. Software for performing automated testing of the integrated circuit using the methods described herein is also contemplated.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
22

BRIEF DESCRIPTION OF THE FIGURES

The foregoing, as well as other objects, features, and advantages of this invention
5 may be more completely understood by reference to the following detailed description
when read together with the accompanying drawings in which:

Figure 1 illustrates the integrated circuit, including the functional pins and the
observability pins of the integrated circuit;

Figure 2 is a block diagram of one embodiment of the observability logic
10 interfacing to one or more functional units and/or internal buses of the integrated circuit;

Figure 3 is a block diagram a system for testing integrated circuits according to
one embodiment of the present invention;

Figure 4 is a block diagram a system for testing integrated circuits according to
another embodiment of the present invention;

15 Figure 5 is a block diagram a system for testing integrated circuits according to
yet another embodiment of the present invention; and

Figure 6 illustrates one embodiment of a computer system capable of performing
automated testing of integrated circuits.

20 While the invention is susceptible to various modifications and alternative forms,
specific embodiments thereof are shown by way of example in the drawings and will
herein be described in detail. It should be understood, however, that the drawings and
detailed description thereto are not intended to limit the invention to the particular form
disclosed, but on the contrary, the intention is to cover all modifications, equivalents, and
25 alternatives falling within the spirit and scope of the present invention as defined by the
appended claims. Note, the headings are for organizational purposes only and are not
meant to be used to limit or interpret the description or claims. Furthermore, note that the
word "may" is used throughout this application in a permissive sense (i.e., having the
potential to, being able to), not a mandatory sense (i.e., must). As used herein, the terms
30 "connected" and "coupled" mean connected, directly or indirectly.

DETAILED DESCRIPTION OF THE EMBODIMENTS

Figure 1 – Integrated Circuit

5 Figure 1 illustrates an integrated circuit 200 which includes logic (referred to as “observability logic”) for testing the integrated circuit according to one embodiment of the present invention. The integrated circuit 200 may be an application specific integrated circuit (ASIC). The integrated circuit 200 may be configured to perform any of various functions. For example, the integrated circuit 200 may be a processor or CPU,
10 a graphics processor, a network processor, an I/O interface, or other type of integrated circuit.

As shown, the integrated circuit 200 may include a plurality of pins 250 and 260 for interfacing with other integrated circuits or devices, i.e., for interfacing with the external world. As shown, the pins 250 and 260 are typically located on the periphery of
15 the integrated circuit 200.

A plurality of the pins may be referred to as functional pins 250. The functional pins 250 provide input/output operations for operation of the integrated circuit 200. In other words, the functional pins 250 are related to the function or operations performed by the integrated circuit 200, and are not specifically related to testing or observability
20 functions (although they may be used in testing the integrated circuit 200).

As shown, the integrated circuit 200 may also include one or more observability pins 260. The observability pins 260 are used for observing or testing internal operations of the integrated circuit 200, i.e., are used for test and debugging purposes. In the current embodiment, the observability logic uses observability 30 pins 260. In one embodiment,
25 5 of the observability pins 260 are designated as input pins (or control pins), and 25 of the observability pins 260 are designated as output pins.

In one embodiment, the integrated circuit 200 may further comprise boundary scan logic and associated pins.

Figure 2

Figure 2 is a block diagram illustrating logic internal to the integrated circuit 200. As shown, the integrated circuit 200 may include a plurality of functional blocks or functional units 206, 210, and 214. Each of the functional units 206, 210, and 214 may include a respective state. For example, functional unit 206 may includes a state referred to as state A, functional unit 210 may have a state referred to as state B, and functional unit 214 may have a state referred to as state C. For example, the functional units 206, 210, and 214 may include state machine logic, wherein the respective state machine logic has a respective state at any given clock cycle. The functional units 206, 210, and 214 may be coupled by respective internal buses 208 and 212. Each internal bus 208 and 212 may comprise a plurality of parallel data lines operating at a single high frequency. The functional units 206, 210, and 214 and the respective internal buses 208 and 212 operate together to perform a function or operation of the integrated circuit 200. Stated another way, the functional units 206, 210, and 214 and internal buses 208 and 212 are not related to the testing operations and are not part of the observability logic.

Figure 2 also shows one embodiment of the observability logic 270. As shown, the observability logic 270 may include selection logic, e.g., a multiplexer 228. The multiplexer 228 operates to select signals from one of the functional units 206, 210 or 214 and/or internal buses 208 or 212 and provide these signals as an output for observation. One or more of the observability pins 260 are inputs provided to select inputs of the multiplexer 228 to select which signals from which of the functional units 206, 210 or 214 and/or internal buses 208 or 212 are to be provided as outputs to the observability pins designated as outputs.

As shown in the embodiment of Figure 2, the multiplexer 228 includes a plurality of inputs which are each coupled to either a respective functional unit (e.g., functional units 206, 210 or 214) or to an internal bus (e.g., internal buses 208 or 214). In the embodiment shown, the multiplexer 228 receives 32 inputs. In other words, the multiplexer 228 can receive signals from 32 different functional units and/or internal buses. A plurality of the observability pins 260 are assigned as output pins 232 and are coupled to an output of the multiplexer 228. In this embodiment, 25 output pins 232 are used, and thus the multiplexer 228 provides a 25 bit output. Accordingly, each of the 32 inputs to the multiplexer 228 has a width of 25 bits.

One or more of the observability pins 260 are assigned as input pins 230 and are used as select signals to the multiplexer 228. The input pins or control pins 230 provide a select signal to the multiplexer 228 to select which of the multiplexer's inputs, i.e., which of the functional unit states or internal bus signals, are provided as an output of the multiplexer 228 to the output pins 232. In the current embodiment, as noted above, 25 of the observability pins 260 are output pins 232 coupled to the output of the multiplexer 228, and 5 of the observability pins 260 are input pins 230 coupled to the select input of the multiplexer 228. As described above, the multiplexer 228 receives 32 25 bit inputs. The five control pins or input pins 230 are used to select among the 32 inputs and provide one of these respective 32 inputs as an output on the 25 output pins 232. The current embodiment provides visibility to an extra 800 internal signals, which is important for system debugging.

In the embodiment shown in Figure 2,

bus0 is coupled to provide state A of functional unit 206;

bus1 is coupled to provide internal bus D 208;

bus2 is coupled to provide state B of functional unit 210;

bus30 is coupled to provide internal bus E 212; and

bus31 is coupled to provide state C of functional unit 214.

The observability logic 270 operates to dynamically and/or in real time display internal values of functional unit states or internal buses on the pins 232 of the integrated circuit 200 while the integrated circuit 200 or system is performing real applications. Signals from an internal bus or internal functional block are preferably provided in real time on the output pins 232, i.e., the signals are provided on the output pins 232 substantially as they are generated, without any intermediate storage or other delay. The observability pins thus operate to present the internal data in real time, which allows substantially immediate observation of changes in the system, not static values as when using boundary scan logic. Observation of changes to the integrated circuit using the test output pins 232 may be performed by a user, or may be analyzed by software executing on a computer system.

Additionally, in one embodiment the observability output pins 232 may be used as trigger states for a logic analyzer. In other words, a logic analyzer may monitor the

observability output pins 232 (and the signal provided on the input pins 230) for signal values of a certain functional unit or internal bus, and may trigger capture of the state of one or more functional pins 250 of the integrated circuit 200 when these signal values are detected. This would allow the logic analyzer to capture a state of the input/output pins (functional pins) 250 with relation to the specific state of an internal state machine or internal bus of the integrated circuit 200. In addition, the logic analyzer may also perform the reverse operation, i.e., monitor certain of the functional pins 250 for signal values and trigger capture of the state of a certain functional unit or internal bus (by applying the appropriate signals to the control pins 230 and capturing the state of the observability output pins 232) when these signal values are detected.

In one embodiment, the input pins are static, and hence the timing of the select inputs to the multiplexer 228 is not critical. This allows for the observability logic 270 to be small and easily designed.

Various other embodiments of the present invention are contemplated. For example, embodiments of the present invention contemplate a greater number of multiplexer inputs, a greater number of multiplexer outputs, a greater number of multiplexers, etc. In addition, based on the needs of the design, the same number of observability pins can be used to expose more internal data. Alternatively, wider buses could be used, with less data displayed externally.

For example, with 30 observability pins, six pins can be assigned as input pins for multiplexer selects and 24 pins used for observed output signals. This provides the user with 2^6 or 64 different 24-bit buses (1536 internal signals). With 30 observability pins, the number of observed signals can be described as:

$$2^{\text{input}} * (30 - \text{input}), \text{ where } 0 < \text{input} < 30.$$

The design can be generalized as to a number n of observability pins where the number of observed internal signals can be derived as follows:

$$2^{\text{input}} * (n - \text{input}), \text{ where } 0 < \text{input} < n.$$

Figure 3

Figure 3 is a block diagram of a system for testing an integrated circuit according to one embodiment of the present invention. In this embodiment, integrated circuit 200

comprises a plurality of functional units or blocks 204, 206, 210, 214, and 218. These functional units are connected via internal buses 208, 212, and 216. In this example, functional units 204 and 220 are input/output (I/O) blocks and are connected to I/O pins 202 and 220, respectively. Under normal operation of integrated circuit 200, data is received on input pins 202 and routed to input block 204. The data may then be forwarded to one or more of the other functional blocks 206, 210, and/or 214 for processing.

In order to effectively test integrated circuit 200, it is desirable to monitor the information that is conveyed on internal buses 208, 212, and 216 while integrated circuit 200 is operating. To accomplish this, buses 208, 212, and 216 are extended (as shown by 222, 224, and 226, respectively) to connect with selection logic or multiplexer 228. Selection logic 228 is in turn connected to test pins 232. Selection logic 228 is controlled by signals from control pins 230.

To enable testing, control pins 230 may be driven by control signals that cause selection logic 228 to select one of internal buses 208, 212, or 216. The signals on the selected bus are then conveyed by selection logic 228 to output test pins 232. While each implementation may vary, in one embodiment only a subset of the signal lines that form internal buses 208, 212, or 216 may be connected to selection logic 228 in order to reduce the number of output pins 232 (for integrated circuit packages with limited numbers of pins). For example, only selected data lines from internal bus 208 may be forwarded to test pins 232, with control signals (e.g., a parity line) from internal bus 208 not being forwarded.

In some embodiments, die space for integrated circuit 200 may be in short supply. In these implementations, it may particularly useful to implement selection logic 228 using smaller transistors, i.e., transistors smaller than those used in the remainder of the integrated circuit 200. Since smaller transistors are typically not able to switch states as quickly as larger transistors, selection logic 228 may be configured to be switched in a non-real time manner (i.e., offline). This potential limitation in switching speed is due to the smaller transistor's more limited ability to sink or source current without excessive heat build up damaging the transistor.

In some embodiments, the control signals driving control pins 230 may be generated using an automated testing program, such as an automated test executive (ATE) program. The testing program may be executed on a computer system that is also connected to test pins 232. The automated testing program may be configured to select a particular internal bus (or functional unit state) for monitoring and then capture the signals from that internal bus (or functional unit state) using test pins 232. The values of the signals captured on the I/O pins or functional pins 250 may be used to trigger a capture of signals on the test pins 232 for a particular functional unit or internal bus, and vice versa.

In some embodiments, once integrated circuit 200 has been determined to be operating properly (i.e., testing is passed and debugging is complete), control pins 230 and test pins 232 may be configured into a low power state when integrated circuit 200 is actually used in a production system. For example, depending on the exact implementation, control pins 230 may be tied to ground or Vcc (e.g., using a pull-up or pull-down resistor) to reduce any potential stasis current that would otherwise cause unnecessary power consumption and heat generation in integrated circuit 200. In other embodiments, control pins 230 and/or test pins 232 may simply be allowed to float. In another embodiment, control pins 230 may be specified to be a certain value in production use, and thus multiplexer 228 may be configured to always provide a selected functional unit state or internal bus as an output. In another embodiment, control pins 230 and/or test pins 232 may be selectively connected, multiplexed, or otherwise configured to connect to other desired input/output signals of the integrated circuit, as shown in Figure 4. Alternatively, in other implementations, if integrated circuit 200 is determined to pass testing and debugging, a final production version of integrated circuit may be manufactured without selection logic 228, control pins 230, and test pins 232. Advantageously, this may allow the use of a smaller integrated circuit package (i.e., with lower pin count).

Figures 4 and 5

Figure 4 is a block diagram of a system for testing an integrated circuit according to another embodiment of the present invention. In the embodiment of Figure 4, interface

logic or output buffers 340, 342 and 344 are coupled to receive the various internal bus signals before they are provided as inputs to the multiplexer 228. These output buffers 340, 342 and 344 each receive a clock or enable signal 338. This operates to synchronize the output of the selection logic or multiplexer 228, as desired. The interface logic or output buffers 340, 342 and 344 may comprise buffers, first-in first-out (FIFO) memories, or flip-flops.

Figure 5 is a block diagram of a system for testing an integrated circuit according to another embodiment of the present invention. In the embodiment of Figure 5, input/output signals 450, which would normally be provided on functional pins of the integrated circuit, are instead connected through an enable buffer 456 to the test or output pins 232. Input pin 458 may provide an enable signal to the enable buffer 456. Thus, when testing is complete, the enable buffer 456 may be enabled to provide the output signals 450 as outputs on the test pins 232. Thus the test pins 232 may effectively “double” as output pins (functional pins) in this embodiment.

A method for testing integrated circuits according to one embodiment of the present invention is also contemplated. In one embodiment, the method includes providing one or more control signals to the observability input or control pins 230 on the integrated circuit 200 being tested. The control signal or signals cause the selection logic 228 within the integrated circuit 200 to select one of a plurality of internal buses and/or functional units for output to the set of parallel output test pins 232 on the integrated circuit 200. The states of the various I/O pins of the integrated circuit 200 may also be monitored. As described above, a logic analyzer or similar hardware and/or software may operate to monitor states of the test pins 232 and use detected states of these pins 232 to trigger capture of the states of certain I/O pins (functional pins) 250. In a similar manner, a logic analyzer or similar hardware and/or software may operate to monitor states of various ones of the functional pins 250 and use detected states of these pins 250 to trigger generation of certain control signals and corresponding capture of the state of the test pins 232, or trigger capture of other functional pins 250. Automated test software may be configured to perform various types of tests and signal captures using the observability logic described herein.

Software for automatically determining the size of multiplexing logic, including number of mux inputs, size of mux inputs, etc. to allow a particular set of internal buses and/or states to be individually monitored is also contemplated. For example, a computer program may comprise instructions executable to 1) receive user-specified information regarding which of a plurality of internal buses on an integrated circuit are to be made available for testing purposes; 2) calculate a size of selection logic and number of control signals required to selectively convey the information on the internal buses to a set of test pins; and 3) provide the results of the calculations to an automated place-and-route routine that determines the physical layout of the integrated circuit. The computer program instructions may be further executable to programmatically generate a specification for the selection logic (e.g., VHDL) based on the user-specified information.

Figure 6 illustrates one embodiment of a computer system 80 capable of performing automated testing of integrated circuits. The computer system 80 may execute automated test software and may interface with the integrated circuit 200, and more particularly with the observability logic 270 comprised in the integrated circuit 200, to conduct various desired tests on the integrated circuit.

Although the embodiments above have been described in considerable detail, other versions are possible. Numerous variations and modifications will become apparent to those skilled in the art once the above disclosure is fully appreciated. It is intended that the following claims be interpreted to embrace all such variations and modifications.